







### FAQ

 I already make a payment how long will it be updated into my account? For cash deposit / online payment / ATM or CDM payment, it will be updated within 3 hours after you faxing in "Payment Submission Form'. Please do polling at your e-pay terminal for account update.

For cheque payment, it will only update once cheque is cleared and shown in e-pay bank statement.

For payment via **JomPAY**, it will be updated in **10 minutes** upon successful transaction. This service is available everyday including Public Holidays.

- 2. Can I check TNG card balance for customer?
  - Yes, if your account comes with TNG service.
  - Press 'Admin' button and key in your sale password
  - Select TNG card balance
  - Place customer TNG card on top of card reader
  - Terminal will display TNG card balance and receipt will be printed out
- How can I know my account credit balance?
   Terminal will show your credit balance every time you did a transaction. Apart from that, you can print
  - credit report to see your available terminal balance.
  - Press 'Admin' button and key in your admin password
  - Press 'Enter'
  - Select '4' for reports
  - Select '4' for others
  - Select '1' for credit
  - Credit Report slip will be printed out
- 4. Im out of paper roll. How can I obtain new paper roll?

Please be informed that there is a new facility in e-pay's terminal to request paper roll effective from Now. You can request paper roll direct **FROM EPAY TERMINAL (Please refer page 10)**, or you can self collect from e-pay HQ @ 16-18, Jln PJS 11/28A, Bandar Sunway

- How can I obtain my account statement, invoice, transaction report, copy of user guide, payment and void submission form?
   You can obtain all the above mentioned by accossing your OCLite opling account.
  - You can obtain all the above mentioned by accessing your OGLite online account.
- 6. How can 1 signup for my OGLite account?

After receiving your e-pay terminal, kindly go to *https://www.oriongateway.com:8443/oglite/index* to signup.

RETAILER QUICK GUIDE TO EPAY TERMINAL







	1.1 Prepaid Mobile M'sia	Page 3
	1.2 Bill Payment	Page 4
	1.3 TNG Reload	Page 5
	1.4 TNG Payment	Page 6
	1.5 Pre Auth	Page 7
	1.6 Pre Auth complete	Page 8
	1.7 Pre Auth Void	Page 9
	1.8 E-Wallet Payment (Sale)	Page 10
	1.9 E-Wallet Payment (Void)	Page 11
	1.10 Re-Print Voucher / Void	Page 12
	1.11 Request Paper Roll	Page 13
2.0	How to make payment	
	2.1 Via Jompay	Page 14
	2.2 Via Cash Deposit/Cheque/Online Payment	Page 15
3.0	Terminal Setup	
	3.1 Long Way Poll (Ethernet)	Page 16
	3.2 Long Way Poll (Modem)	Page 17
	3.3 Long Way Poll (GPRS)	Page 18
4.0	Print Report	
	4.1 Shift Total / Day Total	Page 19
	4.2 End Shift	Page 20
	4.3 End Day	Page 21
5.0	OGL Lite	
	5.1 Retailer Singup	Page 22
	5.2 After Approval	Page 23
6.0	FAQ	Page 24







5.2 - OGL Lite– After approval

### After approval - OGL Lite

1. Once approved, retailer will receive a 'user account creation' email from noreply@ghl.com

### 2. Click the link given to create username.

Dear visitor
To perform user account creation based on your retailer account <b>please</b> click on the following link.
https://www.oriongateway.com:8443/oglite/linkRedirect?a=a4aRIAASkYl2Z% 2FHHa1rWBFy0n5DipD1hkjYY8uUiIfe25pMfZpUci8gyARrC5hxmr4MBvT%2FGhrI% 3D&x=xuarp
Note: This is an automatically generated email, please do not reply.
Thank You.

- 3. Enter the details needed.
- 4. Click 'Request TAC' button to request for TAC.
- 5. Enter the TAC and click 'Submit' button.



Welcome To OGLite

Create New User			
Retailer Ad	count *		
User	Name 📍		
Display	Name *		
Securit	y Text *		
	TAC *		
Pas	sword *		
Retype Pas	sword *		
	Submit	Request TAC	]









# 1.1 - Terminal Function – Sales (Prepaid Mobile M'sia)

	TERMINAL DISPLAY	WHAT TO DO	TERMINAL DISPLAY	WHAT TO DO
	e-pay dd/mm/yy hh:mm N4.0.6B Sale Poll Admin	Press Sale	SALE Hotlink 10 RM10.00	Press Yes to confirm Product Press No to return to main menu
	Sale			
REI	Operator password: *****	Please Key in your sale operator password to proceed Press enter	Printing Receipt	Prepaid Topup Voucher will be printed out
	1 Prepaid Mobile M'sia 2 Prepaid Mobile MVNO 3 e-Wallet 4 Oversea IDD 5 Online Games 6 DD/Internet 7 PTPTN 8 Bill Payment	Select your product by pressing the number keys. Example: Press 1	E-PAY (M) Sdn Bhd TEST 1 16-18, Jalan PJS11/28 46150 Bandar Sunwa Petaling Jaya, Selanga	ЗА, γ, or
	1 DiGi 2 Hotlink 3 Celcom 4 Umobile 5 YES	Select your product by pressing the number keys. Example : Press 2	Terminal ID: 11/10/19	80002603 15:13:13
	1 Hotlink 5		Hotl	link 5
	2 Hotlink 10		01234	56789
	3 Hotlink 30 4 Hotlink 60 5 Hotlink 100	Select your product by pressing the number keys. Example: Press 1	Expires : RM	12/12/12 5.00
			Serial Number :	0123456789
	Sale Available credit: RM1000.00	Press ENTER. (The amount shown is the available credit for the day )	Transaction Number Cashier :	: 0132465789 0002
	Enter to continue		l	
	SALE Hotlink 10 RM10.00	Press Yes to confirm Product Press No to return to main menu	Note: Product No 1 – No (Top up Voucher)	5 will follow the same steps

5.1 - OGL Lite – Retailer Signup

### OGL Lite

- 1. Open a browser and go to https://www.oriongateway.com:8443/oglite/index
- 2. Click 'form'.



3. Fill in the e-form and click 'submit' when done.



Retailer Account *	
First Name *	
Last Name *	
NRIC *	(e.g: 751010536687
Email Address *	
Contact Number *	(e.g: 0121234567)
Invoice address *	
PostCode *	

NOTE: After submitting the e-form, retailer need to wait for approval.

Yes

No





## 1.2 - Terminal Function – Sales (Bill Payment)

TERMINAL DISPLAY	WHAT TO DO	TERMINAL DISPLAY	WHAT TO DO
e-pay dd/mm/yy		SALE	
hh:mm		Amount Range:	
N4.0.6B		10.00-1000.00	
	Press Sale		Key in Amount
		Enter AMT	
Sale Poll Admin		0.00	-
Sale		SALE	Press Yes to confirm
	Please Key in your sale	TNB Bill Payment	Product
	operator password to	RIM10.00	Press No to return to
Operator password:	proceed		mainmenu
	Press enter		
****		Yes No	
1 Prepaid Mobile M'sia		SALE	
2 Prepaid Mobile MVNO		SALE	
3 e-Wallet	Select your product by		Bill Payment Voucher will
4 Oversea IDD	pressing the number keys.		be printed out
6 DD/Internet	Press 8		
7 PTPTN		Printing Receipt	
8 Bill Payment		<u> </u>	
1 Astro			
2 UNIODIIE BIII Payment	Select your product by	E-PAY (M) Sdn Bhd	
4 Maxis Bill Payment	pressing the number keys.	TEST 1	
5 YES Bill Payment	Example : Press 7	16-18, Jalan PJS11/28	Α,
6 Air Selangor		46150 Bandar Sunway	1,
7 TNB Bill Payment		Petaling Jaya, Selango	r
Sale		Terminal ID:	80002603
Suic		11/10/19	15:13:13
Available credit:	Press ENTER.		
RM1000.00	(The amount shown is the		GA
	available credit for the		ONAL BERHAD
	day )		
Enter to continue		INB BIILE	ayment
Sale		RM 1	0.00
	Key in customer bill ac-		
	count number	Account Number :	0123456789
Enter/Swipe Number:	Press enter		
*****			
SALE			/
JALL	Press Yes to confirm Prod-		
Confirm Entry:	uct	Note: NO refund is allow	ved for any bill payment
1000897654	Press No to return to	<u></u> retaina is unov	
	main menu		
Yes No			4





# 4.3 - Print Report (End Day)

TERMIN	AL DISPLAY	WHAT TO DO
e-pay	dd/mm/yy	
	hh:mm	
	N4.0.6B	
		Press Admin
Sale	Poll Admin	
	Admin	
		Please Key in your sale
		operator password to
Oner	rator password	proceed
Oper		Press enter
1 TNG Ca	ard Balance	
2 Report		
3 End Sh	ift	Press 2 to select Report
4 Reprint	t Receipt	
5 Check	TXN Status	
1 Shift To	otal	
2 Day To	tal	Press 3 for end day
3 End Da	ıy	
4 Refund	ł	
5 Others		
	End Day	
Confirm	to reconcile ?	Press Yes
Yes	No	
	End Day	
		Report will be printed out
Printing	report	

,,	Bhd			
TEST 1				
16-18, Jalan PJ	511/28A,			
46150 Bandar S	Sunway,			
Petaling Jaya, S	elangor			
Terminal ID:			80002603	
11/10/19			15:13:13	
*[	DAY TO	TAL*		
Performed By				
Operator ID:			0001	
Operator Name	e :		ADMIN	
Product Type : e-Wallet Payment				
	e wanee	ayinei		
Product	Type	Sold	Total	
Product Brand	Туре	Sold	Total	
Product Brand	Туре	Sold	Total	
Product Brand 	Type PMT	Sold	Total 	
Product Brand 	Type PMT	Sold 3	Total 	
Product Brand TnG eWallet Grand Total :	Type PMT	Sold 3	Total 1.50 1.50	
Product Brand TnG eWallet Grand Total :	Type PMT	Sold 3 3	Total 1.50	
Product Brand TnG eWallet Grand Total :	Type PMT	Sold 3 3	Total 1.50 1.50	





80002603

15:13:13

Total

1.50

1.50

3

3

0002

Sale

Total

1.50

1.50

1





## 1.3 - Terminal Function – TNG Reload

TERMINAL DISPLAY	WHAT TO DO	TERMINAL DISPLAY	WHAT TO DO
e-pay dd/mm/yy hh:mm N4.0.6B Sale Poll Admin	Press Sale	Sale Touch N Go 10 RM10.00	Press Yes to confirm Product Press No to return to main menu
Sale		SALE	
Operator password:	Please Key in your sale operator password to proceed Press enter	Topup Card	Place Touch N Go card the reader
1 Prepaid Mobile M'sia		SALE	
2 Prepaid Mobile MVNO 3 e-Wallet 4 Oversea IDD 5 Online Games 6 DD/Internet 7 PTPTN 8 Bill Payment ♥	Press F4 to view other menu	Printing Receipt	Receipt Voucher will b printed out
1 Other 2 Remittance 3 Request Paper Roll 4 TNG Reload Top UP 5 Touch N Go Payment	Select your product by pressing the number keys. Press 4	E-PAY (M) Sdn Bhd TEST 1 16-18, Jalan PJS11/28A, 46150 Bandar Sunway, Petaling Jaya, Selangor	
1 Touch N Go 10 2 Touch N Go 20 3 Touch N Go 50 4 Touch N Go 100 5 Touch N Go 150 6 Touch N Go 200 7 Touch N Go 500	Select your product by pressing the number keys. Example: Press 1	Terminal ID: 11/10/19 Touch' n Go Rel *RELOAD	80002603 15:13:13 oad 10
Sale Available credit: RM1000.00	Press ENTER. (The amount shown is the available credit for the day )	RM 10.0	0 

# 4.2 - Print Report (End Shift)

E-PAY (M) Sdn Bhd

16-18, Jalan PJS11/28A, 46150 Bandar Sunway, Petaling Jaya, Selangor

15:13:13

11:31:23

Product Type : e-Wallet Payment

Type Sold

PMT

**END SHIFT\*** 

TEST 1

Terminal ID:

Shift Number :

Shift Start :

Shift End :

Product

Brand

TnG eWallet

Grand Total :

Operator ID :

Product

Brand

TnG eWallet

Grand Total :

Operator Name :

**OPERATOR SUMMARY :** 

Product Type : e-Wallet Payment

Type Sold

PMT

11/10/19

TERMINAL DISPLAY	WHAT TO DO
e-pay dd/mm/yy hh:mm N4.0.6B	Press Admin
Sale Poll Admin	
Admin Operator password:	Please Key in your sale operator password to proceed Press enter
1 TNG Card Balance 2 Report	
3 End Shift 4 Reprint Receipt 5 Check TXN Status	Press 3 to end shift
End Shift	
Confirm to reconcile ?	Press yes
Yes No	
End Shift	Report will be printed out
Printing report	

3

3





1.4 - Terminal Function – TNG Payment

TERMINAL DISPLAY	WHAT TO DO	TERMINAL DISPLAY	WHAT TO DO
e-pay dd/mm/yy hh:mm N4.0.6B Sale Poll Admin	Press Sale	SALE Purchase Transaction	Place Touch N Go card on the reader
Sale Operator password: *****	Please Key in your sale operator password to proceed Press enter	SALE Printing Receipt	Receipt Voucher will be printed out
1 Prepaid Mobile M'sia 2 Prepaid Mobile MVNO 3 e-Wallet 4 Oversea IDD 5 Online Games 6 DD/Internet 7 PTPTN 8 Bill Payment ▼	Press F4 to view other menu	E-PAY (M) Sdn Bhd TEST 1 16-18, Jalan PJS11/28A, 46150 Bandar Sunway, Petaling Jaya, Selangor	
1 Other 2 Remittance 3 Request Paper Roll 4 TNG Reload Top UP 5 Touch N Go Payment	Select your product by pressing the number keys. Press 5	Terminal ID: 11/10/19	80002603 15:13:13
1 Touch N Go Payment	Select your product by pressing the number keys. Press 1	Touch' n Go Pay *PAYMEN RM 10.00 	yment T* 0 4R01001500009
Sale Amount Range 0.05 - 1000.00	Key in payment amount Press enter	Transaction Number : Cashier : 	0132465789 0002 SALE
Enter Amt 10.00			





4.1 - Print Report (Shift Total / Day Total)

TERMINAL DISPLAY	WHAT TO DO	E-RAY (M) Sdp Rhd	
e-pay dd/mm/yy		TEST 1	
hh:mm		16-18 Jalan PIS11/28A	
N4.U.6B	Proce Admin	46150 Bandar Sunway	
	FIESS AUTIII	Petaling Java Selangor	
		Terminal ID:	80002603
Sale Poll Admin		11/10/19	15:13:13
Admin		*SHIET TOTAL*	13.13.13
	Please Key in your sale		
	operator password to	Shift Number :	1
Operator password:	proceed Press enter	Shift Start :	15:13:13
	Tress enter		
1 TNG Card Balance			
2 Report	Deves 2 to select Devest		
3 ENO SNIΠ 4 Reprint Receipt	Press 2 to select Report		
5 Check TXN Status			
		E-PAY (M) Sdn Bhd	
		TEST 1	
1 Snift Total 2 Day Total	Proce 1 to soloct - Shift	16-18, Jalan PJS11/28A,	
3 Refund	total. or	46150 Bandar Sunway,	
4 Others	Press 2 to select—Day	Petaling Jaya, Selangor	
	total	Terminal ID:	80002603
		11/10/19	15:13:13
		*DAY TOTAL*	
		Performed By	
		Operator ID:	0002
	Report will be printed out		
Printing report			







dd/mm/yy

hh:mm

N4.2.12B

TERMINAL DISPLAY

e-pay

1 Pre Auth

1 Pre Auth

\*\*\*\*\*

1 e-Wallet

2 Pre Auth Complete

Operator Password :

1 e-Wallet Payment

Pre Auth

Enter/Swipe Number : Pre Auth

Pre Auth

Enter Amt

Confirm Entry :

Yes

Pre Auth



# 1.5 - Terminal Function – Pre Auth (E-Wallet)

WHAT TO DO

Press Other

Press Pre Auth

Press Pre Auth

Press e-Wallet

Key In Sales Password

Press e-Wallet Payment

Key In / Scan Ewallet QR

Key in amount and press

Code

Press Yes

enter

No

0.00



Note : For time being Pre Auth only available for Alipay E-Wallet and selected merchant **ONLY** 

e-pay       dd/mm/yy       press Poll       GPRS Password:       Leave it blank then press enter         Sale       Poll       Admin       Leave it blank then press enter       Leave it blank then press enter         Manual Poll       Press F2 Button       Host IP:       Key in host IP then press enter         Yes       No       Select 4 to choose       Rey in host port then press enter         1 Ethernet       Select 4 to choose       Rey in GPRS dial number       Key in host port then press enter         3 Dialup       Yes       Select 4 to choose       Select 7 wes'       Select 7 wes'         GPRS Dial Number:       Key in GPRS dial number       Connect to Host?       Select 7 wes'         gPRS APN:       Key in GPRS APN then press enter       Manual Poll       Polling Success         GPRS APN:       Key in GPRS APN then press enter       Manual Poll       Polling Success         GPRS Username:       Leave it blank then press enter       GPRS APN       Host IP :         GPRS Username:       Leave it blank then press enter       GPRS APN       Host IP :         GPRS Username:       Leave it blank then press enter       GPRS APN       Host IP :         GPRS Username:       Leave it blank then press enter       Maxis = maxis3g       S8.26.9.22 /         GPRS Username:	TERMINAL DISPLAY	WHAT TO DO	TERMINAL DISPLAY	WHAT TO DO
Manual Poll Connect to Host?       Press F2 Button       Key in host IP then press enter         Yes       No         1 Ethernet 2 Modem 3 Dialup 4 GPRS       Select 4 to choose GPRS       Image: Connect to Host?       Key in host port then press enter         GPRS Dial Number: *99#       Key in GPRS dial number then press enter       Connect to Host?       Select 'Yes'         GPRS APN:       Key in GPRS APN then press enter       Manual Poll Yes       Select 'Yes'         GPRS Lisername:       Leave it blank then press enter       GPRS APN       Manual Poll Yes       Polling Success Printing Report         GPRS Username:       Leave it blank then press enter       GPRS APN       Host IP : Maxis = maxis3g Celcom = celcomag       Host IP : Host IP : Host Port :	e-pay dd/mm/yy hh:mm N4.0.6B Sale Poll Admin	Press Poll	GPRS Password:	Leave it blank then press enter
1 Ethernet 2 Modem 3 Dialup 4 GPRS       Select 4 to choose GPRS       key in host port then press enter         GPRS Dial Number: *99#       Key in GPRS dial number then press enter       Connect to Host? Yes       Select 'Yes'         GPRS Dial Number: *99#       Key in GPRS dial number then press enter       Connect to Host? Yes       Select 'Yes'         GPRS APN:       Key in GPRS APN then press enter       Manual Poll       Polling Success Printing Report         GPRS Username:       Leave it blank then press enter       GPRS APN       Host IP : Maxis = maxis3g Celcom = celcom3g	Manual Poll Connect to Host? Yes No	Press F2 Button	Host IP:	Key in host IP then press enter
GPRS Dial Number:       Key in GPRS dial number then press enter       Connect to Host?       Select 'Yes'         'Yes       No         GPRS APN:       Key in GPRS APN then press enter       Manual Poll       Polling Success         GPRS APN:       Key in GPRS APN then press enter       Complete success       Polling Success         GPRS Username:       Leave it blank then press enter       GPRS APN       Host IP :         GPRS Username:       Leave it blank then press enter       Maxis = maxis3g       S8.26.9.22 /         GPRS Username:       Leave it blank then press enter       Maxis = maxis3g       S8.26.9.22 /	1 Ethernet 2 Modem 3 Dialup 4 GPRS	Select 4 to choose GPRS	Host Port: 8090	Key in host port then press enter
GPRS APN:       Key in GPRS APN then press enter       Manual Poll       Polling Success         Complete success Printing Report       Complete success       Polling Success         GPRS Username:       Leave it blank then press enter       GPRS APN       Host IP :         Maxis = maxis3g       58.26.9.22 /       219.92.28.137         Host Dept :       Host Dept :       Host Dept :	GPRS Dial Number: *99#	Key in GPRS dial number then press enter	Connect to Host? Yes No	Select 'Yes'
GPRS Username:       Leave it blank then press enter       GPRS APN       Host IP :         Maxis = maxis3g       58.26.9.22 /         Celcom = celcom3g       219.92.28.137         Host Port :       Host Port :	GPRS APN:	Key in GPRS APN then press enter	Manual Poll Complete success Printing Report	Polling Success
	GPRS Username:	Leave it blank then press enter	GPRS APN Maxis = maxis3g Celcom = celcom3g	Host IP : 58.26.9.22 / 219.92.28.137 Host Port :

Tunetalk = tunetalk

UMobile = my3g

8090





1.6 - Terminal Function – Pre Auth Complete (E-Wallet)

TERMINAL DISPLAY	WHAT TO DO
e-pay dd/mm/yy	
hh:mm	
N4.2.12B	
	Press Other
Sale Other Poll Admin	
1 Pre Auth	
	Press Pre Auth
1 Pre Auth	
2 Pre Auth Complete	
2 me nutil complete	Press Pre Auth Complete
Pre Auth Complete	
Operator Password :	Key In Sales Password
****	
1 e-Wallet	
	Press e-Wallet
1 e-Wallet Payment	
	Proce o Wallot Paymont
	r ress e-wanet Payment
Pre Auth Complete	
Enter TXN Ref :	Key In TXN Ref at receipt
*****	(Key in full TXN Ref)
Pre Auth Complete	Key in amount and press
	enter
	(Amount should not be
Enter Amt	higher than the pre auth)
0.00	
U.UU Pre Auth	
	Press ves to print
	customer conv
Print Customor Conv	customer copy
Finit Customer Copy	
Yes No	

Epay TS 9	
GHL Office	
Terminal ID:	80014095
03/10/19	14:12:37
Alipay eWa * Pre Auth Con RM **.*	allet nplete *
TXN Ref:	*******
TXN Ref: Transaction Number:	*******
TXN Ref: Transaction Number: Operator ID:	******** *****************************

Note : For time being Pre Auth only available for Alipay E-Wallet and selected merchant **ONLY** 





# 3.2 - Terminal Setup – Long Way Poll (Modem)

TERMINAL DISPLAY	WHAT TO DO	TERMINAL DISPLAY	WHAT TO DO
e-pay dd/mm/yy hh:mm N4.0.6B	Press Poll	Ignore Dial Tone:	Select 'Yes'
Sale Poll Admin		Yes No	
Manual Poll Connect to Host?	Press F2 Button	Connect to Host?	Select 'Yes'
Yes No		Yes No	
1 Ethernet 2 Modem 3 Dialup 4 GPRS	Select 2 to choose Modem	Manual Poll Complete success Printing Report	Polling successful.
Prefix:	Key in PABX no (if any) follow by comma, then press enter	For server number, please check with Epay CS at 03-56236000	
Server Number:	Key in PAD number (according to state) then press enter.	If polling not success please call Epay CS at 03-56236000 for troubleshooting purposes	



Host Port:

Yes

Connect to Host?

Manual Poll

Complete success Printing Report...







## 1.7 - Terminal Function – Pre Auth Void (E-Wallet)

TERMINAL DISPLAY	WHAT TO DO	Т
e-pay dd/mm/yy		
hh:mm		
N4.2.12B	Press Admin	G
		Te
Sale Other Poll Admin		03
Admin	Key In Admin Password	
Operator Password :		
*****		
1 Operator Maint.	Press Void Sale	
2 Enable Demo Mode		
3 Void Sale		
4 Reports		
6 Reprint Receipt		
1 Void Pin	Press Pre Auth	
2 Top up		Q
3 Payment		ТХ
4 Pre Auth		Tr
1 e-Wallet	Press e-Wallet	
1 e-Wallet Payment	Press e-Wallet Payment	
Void Pre Auth		N
	Key In TXN Ref at receipt	0
Enter TXN Ref:	(Key in full TXN Ref)	ar
*****		
Void Pre Auth		
	Key In Transaction	
Enter Transaction #:	Number	
***		
Void Pre Auth		
	Key in amount and press	
	enter	
Enter Amt		



lote : For time being Pre Auth only available for Alipay E-Wallet nd selected merchant ONLY

	3.1	- Terminal Setup – Long Way Pi	oll (Ethernet)
TERMINAL DIS	SPLAY	WHAT TO DO	
e-pay	dd/mm/yy hh:mm N4.0.6B	Press Poll	
Sale Poll	Admin		
Manua	l Poll	Press F2 Button	
Connect t	o Host?		
Yes	No		
1 Ethernet 2 Modem 3 Dialup 4 GPRS		Select 1 to choose Ethernet	
Host IP:		Key in host IP then press	Host IP

enter

Key in host port then

press enter.

Select 'Yes'

Polling successful.

58.26.9.22

8090

No

st IP : 58.26.9.22 / 219.92.28.137

Host Port: 8090

If polling not success please call Epay CS at 03-56236000 for troubleshooting purposes





## 1.8 - Terminal Function – E-Wallet Payment (Sale)

TERMINAL DISPLAY	WHAT TO DO	TERM	INAL DISPLAY	WHAT TO DO
e-pay dd/mm/yy			Sale	
hh:mm		Print	Customer Copy:	Print Customer Copy
N4.2.12B	Dress Cala			
	Press Sale			
Sale Other Poll Admin		Yes	No	
Jale	Diagon Kaulin wave as a			
Operator password:	operator password to proceed			
****	Press enter	Г	Technical Support 9	
1 Pay By GHL		1	Fnav TS 9	
2 Prepaid Mobile M'sia	Dross Day Dy CUI		GHL Office	
4 e-Wallet	Fless Pay by GHL		Terminal ID:	80014095
5 Oversea IDD 6 Online Games			03/10/19	14:12:37
7 DD/Internet				
Sale				え
Enter/Swipe Number :	Scan/Keyin QR Code			
			AI	ipay
			Alipay e	Wallet
Sale		1	* PAYM	ENT *
Confirm Entry: 123456798	Press Yes		RM **	* **
Yes No Sale			TXN Ref:	******
Suic			Transaction Number:	******
	Keyin Payment Amount		Operator ID:	****
Enter Amt				
0.00				
Sale		]		
	Receipt Rrint Out		. /	
			$\searrow$	
			$\smile$	
Printing Receipt		]		





## 2.2 - How to make payment via cash deposit/cheque/online payment

•

1. Payment Channel

Cash Deposit / Cheque Bank in / Online Payment You can bank in cash or cheque/ transfer payment to our bank acct at: MBB: 5123 – 1610 – 3965

CIMB: 800 - 306 - 3975 PBB: 3105 - 615 - 724

2. Payment Update

After payment has been made, kindly update e-pay using 'Payment Submission Form' provided. Fill up the form and attach with a copy of your payment / bank in

slip. Then email or fax to e-pay Email: payment@ghl.com Fax: 03 5636 6966 Call in: 03-5623 6000 SMS: 012-630 4195

**Note:** Please write remark on your 'Payment Submission Form' whether it is for e-pay main account payment or TNG payment. If no remark provided, all payment will go to e-pay main account and payment can't be transfer to TNG account. 3. Minimum Payment/Reload Amount

Prepaid Account Minimum amount Reload

- Main- minimum RM500once chq clear
- TNG- minimum RM300

Postpaid Account (petro station / postpaid account)

- Main- no minimum payment (follow invoice)
- TNG- minimum RM500

Prepaid Account (petromart convert to prepaid)

- Main- Minimum RM500
- TNG- Minimum RM300

Note : Payment by chq we will update once chq clear











### 1.9 - Terminal Function – E-Wallet Payment (Void)

TERMINAL DISPLAY	WHAT TO DO	TERMINAL DISPLAY	WHAT TO DO
e-pay dd/mm/yy		Void Payment	
hh:mm			
N4.2.12B	Press Admin	Print Customer Copy:	Print Customer Copy
Sale Other Poll Admin		Yes No	
Admin	Key In Admin Password		-
Operator Password : ******			
		Technical Support 9	
1 Operator Maint.	Press Void Sale	Epay TS 9	
2 Enable Demo Mode		GHL Office	
3 Void Sale		Terminal ID:	80014095
6 Reports		03/10/19	14:12:37
1 Void Pin	Press Void Payment		
2 Void Top up		マ	
3 Void Payment			
4 Pre Auth		Alipa	ay
		Alipay eW	/allet
1 By TXN Ref	Press Either TXN Ref or	RM **.	**
2 By TXN Num	TXN Num	* Void Payı	ment *
	Ex : Press TXN Num		
Void Payment		Transaction Number :	*****
volu i ayment	Enter Transaction	TXN Ref:	*****
Enter Transaction #:	Number	Operator ID :	*****
			ADMIN
2			
Void Payment		1	
	Receipt Print Out		/
Printing Receipt			
· · · · · · · · · · · · · · · · · · ·			

Simple steps making payment with JomPAY:





2.1 - How to make payment with JomPAY

PAY

STEP 1 Look for the JomPAY logo, Biller Code, Ref-1 & Ref-2 on your Bills or Invoices.

STEP 2 Logon to Internet or Mobile Banking and look for JomPAY - Bill Payment

: <Please key in your e-pay account number>

: <Please key in payment will be for Main or TNG>



Enter Biller Code: [Refer bill], Ref-1: [Refer bill] Ref-2: [Payment for Main or TNG]

Proceed with Payment from your Savings or Current Account

Details to key-in for Step 3 as per below:



: 2360

JomPAY Logo Biller Code Ref -1 Ref -2

Example:

For payment to account		For TNG payment	
JomPAY logo	Jompay	JomPAY logo	JOMPAY
Biller Code	: 2360	Biller Code	: 2360
Ref -1	: 201842	Ref -1	: 201842
Ref -2	: Main	Ref -2	: TNG

### Note:

1. Account will be updated within 10minutes after payment has been done. Merchant will receive SMS or email notification once payment has been updated.





WHAT TO DO

1.10 - Terminal Function – Re-Print Voucher (For Void Purposes)

TERMINAL DISPLAY

**Note:** "Reprint Receipt" function can only capture the previous transaction <u>ONLY</u>, therefore <u>MUST</u> be printed immediately after the faulty voucher is printed.

You have to use the 'Void Request Form' provided. Fill up the form and attach with the original voucher as well as duplicate copy of the voucher. Then email or fax to e-pay within 30days from the date printed. The company will not entertain cancellation request for PINS printed more then 30days.

### Email: void@ghl.com Fax: 03-7493 3110 SMS: 012-630 4195

51415. 012 050 4155		
Tesso Kaland 981 KJ 881 Let PT 37262 8 11156 Marin Alanos Bautans Itolano. Matawa Salanos Testaal II: 2200001 89/15-07 15/28/04		1 Touch N Go Card b 2 Report 3 End Shift 4 Reprint Receipt 5 Check TXN Status
Celcom AT 10 w DUPLICATE w Serial Nuber: 300001000 Transation Nuber: 800000000 Transation Anount: 8018.00 = DUPLICATE #	Will provide information for Serial Number, Transaction number, and amount, but no PIN number will be provided	REPRINT RECEIL
For Voiding Pursose Only. Not for Resale	Voucher will indicate it is for Void Only, Not for Sale	Printing Receipt

e-pay dd/mm hh: N4.0	/yy mm D.6B Press admin
Sale Poll Adr	nin
Admin Operator password	Please Key in sale opera- tor password to proceed I: Press enter
1 Touch N Go Card bala 2 Report 3 End Shift 4 Reprint Receipt 5 Check TXN Status	Select no 4 to choose reprint receipt
REPRINT RECEIPT	Duplicate voucher will be printed out

#### VOID PROCESS

(i) Reason: Printer out of paper/Paper Stuck/Printing Error

Procedure: - Immediately print a duplicate voucher from e-pay terminal - Proceed to print new voucher for the customer

- Fill up "Void Request Form" & send it to e-pay via fax or email
- Ensure to punch 3 holes at the PIN area (for security purpose)

& ensure to use 1 void form for 1 voucher

(ii) Reason: Voucher Blur/Reload Pin not clear/Reload Pin cant be activated Procedure: - Request back the original voucher from the customer

- Immediately print a duplicate voucher from e-pay terminal
- Proceed to print new voucher for the customer
- Fill up "Void Request Form" & send it to e-pay via fax or email
- Ensure to punch 3 holes at the PIN area (for security purpose) & ensure to use 1 void form for 1 voucher





# 1.11 - Request Paper-roll

TERMINAL DISPLAY	WHAT TO DO	TERMINAL DISPLAY	WHAT TO DO
e-pay dd/mm/yy hh:mm N4.0.6B	Press Sale	Sale Confirm entry: 123456	Select 'Yes' to confirm account number
Sale Poll Admin		Yes No	
Sale Operator password:	Please Key in sale opera- tor password to proceed Press enter	Sale Request Paper Roll: Yes No	Select 'Yes' to confirm the request
1 Prepaid Mobile M'sia 2 Prepaid Mobile MVNO 3 e-Wallet 4 Oversea IDD 5 Online Games 6 DD/Internet 7 PTPTN 8 Bill Payment	Press F4 to view other menu	Sale Printing Receipt	Receipt voucher will be printed out
1 Other 2 Remittance 3 Request Paper Roll 4 TNG Reload Top UP 5 Touch N Go Payment	Press 3 to select - Request Paper Roll	E-PAY (M) Sdn Bhd TEST 1 16-18, Jalan PJS11/28A, 46150 Bandar Sunway, Petaling Java Selangor	
Sale Available Credit: PAPERROLL: 1.00 Enter to continue	Press ENTER to continue	Terminal ID: 11/10/19 Request Pape *RECEIPT	80002603 15:13:13 <b>r Roll</b> *
Sale Enter/Swipe Number: 123456	Key in retailer account number Press enter	RM 0.00  Account Number : TXN Ref :	132456 0132465789